## RF-BRIDGE | PIR2 | DW1-RF

## **RF BRIDGE AND SENSORS**



## SPECIFICATIONS

Model	RF-BRIDGE	PIR2	DW1-RF
Туре	433MHz RF Bridge	433.92MHz RF PIR Motion Sensor	Magnetic Door/ Window Alarm Sensor
Additional Features	Fire Alarm Push (Optional) Anti-Theft Alarm Push (Optional) Support 4x Devices (RM433 RF/ Alarms) Set 8x Schedules Support Magnetic Door Sensor Support Body IR Sensor	The motion detector can work with the Sonoff RF-BRIDGE, providing human detected alarm message push to your phone.	The door alarms can work with Sonoff RF Bridge 433. DW1 door alarm sensor detects the opening status and immediately sends alarm notification message to the app.
RF	433 MHz	-	-
Power Supply	USB 5V	-	-
Wireless Standard	WiFi 802.11b/g/n, 433.92MHz	433MHz	433MHz
Battery	-	AAA 3Vcc(2x1.5Vcc)	12V(27A)
Dimensions	62 x 62 x 20 mm	137 x 61 x 43 mm	92 x 57 x 28 mm
Weight	45g	89g	45g
Material	ABS VO	ABS VO	ABS VO
Certification	CE	-	-

\*All product specifications and product images are subject to change without notice.



CONTACT US Website www.cme.co.za E-mail sales@cme.co.za Tel no 012 666 9066/8 **CENTURION** 254 Lochner Road Raslouw, Centurion Gauteng, South Africa

